



668A

Technical data

Line search (SCAN)	Find out the desired cable from a large number of cables.
Cable proofreading (TEST)	Fast measurement of open circuit, short circuit, sequence.
Line voltage test (VOLT)	Measuring the working voltage and positive or negative of phone line.
Continuity test (OHM)	Checking the phone which is under open circuit or short circuit. (Phone line isn't connected to any live equipment)
Torch function	Super bright and white light torch function
Adjustable sensitivity	The volume can be adjusted according to your need when using it.
Headset function	In noisy occasions, headphones can be worn to work.
Frequency conversion of line signal	You can set different frequencies to find lines.
Weak current-turn on test	Can be connected to the Phone line / Ethernet switch/ Router/ Line hunting when the PC terminal is power on. The measured voltage should not exceed 48V.

ELECTRIC STATIC CHARACTERISTIC

Current	transmit currents≤45mA, receive currents≤100mA
Battery	receiver 9V battery; transmitter AA 1.5V battery *3
Transmission distance of hunting line	≥3km
Safety	safe to use (the probe can directly contact the exposed metal wire)

Technical indicators

Hunting line function	√
Paired function	√
Continuity test of short circuit	√
Line voltage	√
Sensitivity adjustable	√
Torch	√
Display	LED light
Distance of hunting line	3 km
Output signal level	Approx 23Vp-p (frequency adjustable)
Other function	Energy saving design, sensitivity adjustable, low voltage detection, headset function.
Packing	Color box ; tool bag